

# Yuasa Technical Data Sheet

## Yuasa SWL2250FR Industrial VRLA Battery



### Specifications

Nominal voltage (V)	12
10-min rate Constant Power to 9.6V at 20°C (Watts per Block)	2250
10-min rate Constant Power to 1.6V/cell at 20°C (W/Cell)	375
20-hr rate Capacity to 10.5V at 20°C (Ah)	86.0
10-hr rate Capacity to 10.8V at 20°C (Ah)	76

### Dimensions

Length (mm)	380 (±0.7)
Width (mm)	166 (±0.5)
Height (mm)	174 (±0.5)
Mass (kg)	27.5

### Terminal Type

Threaded terminal - (M=Male or F=Female)	M8 (F)
Torque (Nm)	6

### Operating Temperature Range

Storage (in fully charged condition)	-20°C to +50°C
Charge	-15°C to +50°C
Discharge	-20°C to +60°C

### Storage

Capacity loss per month at 20°C (% approx.)	3
---	---

### Case Material

Standard	ABS (UL94:V0)
----------	---------------

### Charge Voltage

Float charge voltage at 20°C (V)/Block	13.65 (±1%)
Float charge voltage at 20°C (V)/Cell	2.275 (±1%)
Float Chg voltage tmp correction factor from std 20°C (mV)	-3
Cyclic (or Boost) charge Voltage at 20°C (V)/Block	14.5 (±3%)
Cyclic (or Boost) charge Voltage at 20°C (V)/Cell	2.42 (±3%)
Cyclic Chg voltage tmp correction factor from std 20°C (mV)	-4

### Charge Current

Float charge current limit (A)	No limit
Cyclic (or Boost) charge current limit (A)	19

### Maximum Discharge Current

1 second (A)	800
1 minute (A)	500

### Short-Circuit Current & Internal Resistance

Internal resistance - according to EN IEC 60896-21 (m)	10.49
Short-Circuit current - according to EN IEC 60896-21 (A)	1442

### Impedance


Measured at 1 kHz	<5
-------------------	----

### Design Life & Approvals

EUROBAT Classification: High Performance	10 to 12
Yuasa design life at 20°C (yrs)	up to 10



### Layout



### 3rd Party Certifications

ISO9001 - Quality Management Systems  
ISO14001 - Environmental Management Systems  
EN 18001 OHSAS Management Systems  
UNDERWRITERS LABORATORIES Inc.



## Safety

### Installation

Can be installed and operated in any orientation except permanently inverted.

### Handles

Batteries must not be suspended by their handles (where fitted).

### Vent valves

Each cell is fitted with a low pressure release valve to allow gasses to escape and then reseal.

### Gas release

VRLA batteries release hydrogen gas which can form explosive mixtures in the air. Do not place inside a sealed container.

### Recycling

YUASA's VRLA batteries must be recycled at the end of life in accordance with local and national laws and regulations.

